74HC03; 74HCT03 Quad 2-input NAND gate; open-drain output Rev. 4 — 27 November 2015

Product data sheet

General description 1.

The 74HC03; 74HCT03 is a quad 2-input NAND gate with open-drain outputs. Inputs include clamp diodes that enable the use of current limiting resistors to interface inputs to voltages in excess of V_{CC}.

Features and benefits 2.

- Input levels:
 - For 74HC03: CMOS level
 - For 74HCT03: TTL level
- Complies with JEDEC standard no. 7A
- ESD protection:
 - HBM JESD22-A114F exceeds 2000 V
 - MM JESD22-A115-A exceeds 200 V
- Multiple package options
- Specified from -40 °C to +85 °C and from -40 °C to +125 °C

Ordering information 3.


Table 1. **Ordering information**

Type number	Package									
	Temperature range	Name	Description	Version						
74HC03D	–40 °C to +125 °C	SO14	plastic small outline package; 14 leads; body width	SOT108-1						
74HCT03D			3.9 mm							
74HC03DB	–40 °C to +125 °C	SSOP14	plastic shrink small outline package; 14 leads; body	SOT337-1						
74HCT03DB			width 5.3 mm							
74HC03PW	–40 °C to +125 °C	TSSOP14	plastic thin shrink small outline package; 14 leads;	SOT402-1						
74HCT03PW			body width 4.4 mm							




Quad 2-input NAND gate; open-drain output

4. Functional diagram



5. Pinning information

5.1 Pinning



5.2 Pin description

Table 2. Pin description		
Symbol	Pin	Description
1A to 4A	1, 4, 9, 12	data input
1B to 4B	2, 5, 10, 13	data input
1Y to 4Y	3, 6, 8, 11	data output
GND	7	ground (0 V)
V _{cc}	14	supply voltage

74HC_HCT03
Product data sheet

Quad 2-input NAND gate; open-drain output

6. Functional description

Table 3. F	unction	table ^[1]
------------	---------	----------------------

Input	Output	
nA	nB	nY
L	L	Z
L	Н	Z
Н	L	Z
Н	Н	L

[1] H = HIGH voltage level; L = LOW voltage level; Z = high-impedance OFF-state.

7. Limiting values

Table 4.Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134). Voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions		Min	Max	Unit
V _{CC}	supply voltage			-0.5	+7	V
Vo	output voltage		<u>[1]</u>	-0.5	+7	V
I _{IK}	input clamping current	$V_{\rm I} < -0.5$ V or $V_{\rm I} > V_{\rm CC}$ + 0.5 V	<u>[1]</u>	-	±20	mA
Ι _{ΟΚ}	output clamping current	V _O < -0.5 V	<u>[1]</u>	-	-20	mA
I _O	output current	-0.5 V < V _O		-	-25	mA
I _{CC}	supply current			-	50	mA
I _{GND}	ground current			-50	-	mA
T _{stg}	storage temperature			-65	+150	°C
P _{tot}	total power dissipation		[2]			
	SO14 and (T)SSOP14 packages			-	500	mW

[1] The input and output voltage ratings may be exceeded if the input and output current ratings are observed.

[2] For SO14 package: Ptot derates linearly with 8 mW/K above 70 °C.

For (T)SSOP14 packages: Ptot derates linearly with 5.5 mW/K above 60 °C.

8. Recommended operating conditions

Table 5. Recommended operating conditions

Voltages are referenced to GND (ground = 0 V)

Symbol	Parameter	Conditions		74HC03			74HCT03		
			Min	Тур	Max	Min	Тур	Max	
V _{CC}	supply voltage		2.0	5.0	6.0	4.5	5.0	5.5	V
VI	input voltage		0	-	V _{CC}	0	-	V _{CC}	V
Vo	output voltage		0	-	V _{CC}	0	-	V _{CC}	V
T _{amb}	ambient temperature		-40	+25	+125	-40	+25	+125	°C
$\Delta t / \Delta V$	input transition rise and fall rate	$V_{CC} = 2.0 V$	-	-	625	-	-	-	ns/V
		$V_{CC} = 4.5 V$	-	1.67	139	-	1.67	139	ns/V
		$V_{CC} = 6.0 V$	-	-	83	-	-	-	ns/V

74HC HCT03

Quad 2-input NAND gate; open-drain output

9. Static characteristics

Table 6. Static characteristics

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions		25 °C		−40 °C t	o +85 °C	–40 °C to +125 °C		Unit
			Min	Тур	Max	Min	Max	Min	Max	
74HC03										
V _{IH}	HIGH-level	V _{CC} = 2.0 V	1.5	1.2	-	1.5	-	1.5	-	V
	input voltage	V _{CC} = 4.5 V	3.15	2.4	-	3.15	-	3.15	-	V
		V _{CC} = 6.0 V	4.2	3.2	-	4.2	-	4.2	-	V
V _{IL}	LOW-level	V _{CC} = 2.0 V	-	0.8	0.5	-	0.5	-	0.5	V
	input voltage	V _{CC} = 4.5 V	-	2.1	1.35	-	1.35	-	1.35	V
		V _{CC} = 6.0 V	-	2.8	1.8	-	1.8	-	1.8	V
V _{OL}	LOW-level	$V_{I} = V_{IH} \text{ or } V_{IL}$								
	output voltage	$I_{O} = 20 \ \mu A; V_{CC} = 2.0 \ V$	-	0	0.1	-	0.1	-	0.1	V
		I_{O} = 20 μ A; V_{CC} = 4.5 V	-	0	0.1	-	0.1	-	0.1	V
		$I_{O} = 20 \ \mu A; V_{CC} = 6.0 \ V$	-	0	0.1	-	0.1	-	0.1	V
		I_{O} = 4.0 mA; V_{CC} = 4.5 V	-	0.15	0.26	-	0.33	-	0.4	V
		$I_{O} = 5.2 \text{ mA}; V_{CC} = 6.0 \text{ V}$	-	0.16	0.26	-	0.33	-	0.4	V
I	input leakage current	$V_I = V_{CC}$ or GND; $V_{CC} = 6.0 V$	-	0.1	-	-	±1	-	±1	μA
I _{OZ}	OFF-state output current	per input pin; $V_I = V_{IL}$; $V_O = V_{CC}$ or GND; other inputs at V_{CC} or GND; $V_{CC} = 6.0 \text{ V}$; $I_O = 0 \text{ A}$	-	-	±0.5	-	±5.0	-	±10	μA
I _{CC}	supply current		-	2.0	-	-	20	-	40	μA
CI	input capacitance		-	3.5	-	-	-	-	-	pF
74HCT0	3		1		1	1	1	1		
V _{IH}	HIGH-level input voltage	V_{CC} = 4.5 V to 5.5 V	2.0	1.6	-	2.0	-	2.0	-	V
V _{IL}	LOW-level input voltage	V_{CC} = 4.5 V to 5.5 V	-	1.2	0.8	-	0.8	-	0.8	V
V _{OL}	LOW-level	$V_{I} = V_{IH} \text{ or } V_{IL}; V_{CC} = 4.5 \text{ V}$								
	output voltage	I _O = 20 μA	-	0	0.1	-	0.1	-	0.1	V
		I _O = 4.0 mA	-	0.15	0.26	-	0.33	-	0.4	V
I	input leakage current	$V_I = V_{CC}$ or GND; $V_{CC} = 5.5 V$	-	-	±0.1	-	±1	-	±1	μA
loz	OFF-state output current	per input pin; $V_I = V_{IL}$; $V_O = V_{CC}$ or GND; other inputs at V_{CC} or GND; $V_{CC} = 5.5$ V; $I_O = 0$ A	-	-	±0.5	-	±5.0	-	±10	μA

Rev. 4 — 27 November 2015

Quad 2-input NAND gate; open-drain output

Table 6. Static characteristics ...continued

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol Parameter		Conditions	25 °C		–40 °C to +85 °C		–40 °C to +125 °C		Unit	
			Min	Тур	Max	Min	Max	Min	Max	
I _{CC}	supply current		-	-	2.0	-	20	-	40	μA
ΔI _{CC}	additional supply current	per input pin; $V_I = V_{CC} - 2.1 \text{ V}; I_O = 0 \text{ A};$ other inputs at V_{CC} or GND; $V_{CC} = 4.5 \text{ V}$ to 5.5 V	-	100	360	-	450	-	490	μA
CI	input capacitance		-	3.5	-	-	-	-	-	pF

10. Dynamic characteristics

Table 7. Dynamic characteristics

GND = 0 V; $C_L = 50$ pF; for test circuit, see <u>Figure 7</u>.

Symbol	Parameter	Conditions			25 °C		-40 °C to	o +125 ℃	Unit
			_		Тур	Max	Max (85 °C)	Max (125 °C)	
74HC03									
t _{pd} propagation dela	nA, nB to nY; see Figure 6	<u>[1]</u>							
		$V_{CC} = 2.0 V$		-	28	95	120	145	ns
		V _{CC} = 4.5 V		-	10	19	24	29	ns
		$V_{CC} = 5.0 \text{ V}; \text{ C}_{L} = 15 \text{ pF}$		-	8	-	-	-	ns
		$V_{CC} = 6.0 V$		-	8	16	20	25	ns
t _t	transition time	see <u>Figure 6</u>	[2]						
		$V_{CC} = 2.0 V$		-	19	75	95	110	ns
		V _{CC} = 4.5 V		-	7	15	19	22	ns
		$V_{CC} = 6.0 V$		-	6	13	16	19	ns
C _{PD}	power dissipation capacitance	per package; $V_I = GND$ to V_{CC}	<u>[3]</u>	-	4	-	-	-	pF

Quad 2-input NAND gate; open-drain output

Symbol	Parameter	Conditions		25 °C			-40 °C to	o +125 ℃	Unit
			Min	Тур	Max	Max (85 °C)	Max (125 °C)		
74HCT03	3	1							
t _{pd} propagation delay	propagation delay	nA, nB to nY; see Figure 6	<u>[1]</u>						
		V _{CC} = 4.5 V		-	12	24	30	36	ns
		V _{CC} = 5.0 V; C _L = 15 pF		-	10	-	-	-	ns
t _t	transition time	V _{CC} = 4.5 V; see <u>Figure 6</u>	[2]	-	7	15	19	22	ns
C _{PD}	power dissipation capacitance	per package; V _I = GND to V _{CC} – 1.5 V	<u>[3]</u>	-	4	-	-	-	pF

Table 7. Dynamic characteristics ... continued $GND = 0 V \cdot C_{i}$ = 50 pF; for test circuit, see Figure 7

[1] t_{pd} is the same as t_{PLZ} and t_{PZL} .

[2] t_t is the same as t_{THL} .

[3] C_{PD} is used to determine the dynamic power dissipation (P_D in μW):

 $P_D = C_{PD} \times V_{CC}^2 \times f_i \times N + \sum (C_L \times V_{CC}^2 \times f_o)$ where:

 f_i = input frequency in MHz;

 $f_o = output frequency in MHz;$

 C_L = output load capacitance in pF;

V_{CC} = supply voltage in V;

N = number of inputs switching;

 $\Sigma (C_L \times V_{CC}^2 \times f_o)$ = sum of outputs.

11. Waveforms




Table 8. **Measurement points**

Туре	Input	Output			
	V _M	V _M	V _X		
74HC03	0.5V _{CC}	0.5V _{CC}	0.1V _{CC}		
74HCT03	1.3 V	1.3 V	0.1V _{CC}		

74HC_HCT03 **Product data sheet**

6 of 14

Nexperia

74HC03; 74HCT03

Quad 2-input NAND gate; open-drain output




Table 9. Test data

Туре	Input		Load	S1 position	
	VI	t _r , t _f	CL	RL	t _{PZL} , t _{PLZ}
74HC03	V _{CC}	6 ns	15 pF, 50 pF	1 kΩ	V _{CC}
74HCT03	3.0 V	6 ns	15 pF, 50 pF	1 kΩ	V _{CC}

Quad 2-input NAND gate; open-drain output

12. Package outline




Fig 8. Package outline SOT108-1 (SO14)

All information provided in this document is subject to legal disclaimers.

74HC_HCT03

Quad 2-input NAND gate; open-drain output




Fig 9. Package outline SOT337-1 (SSOP14)

All information provided in this document is subject to legal disclaimers.

74HC_HCT03

Quad 2-input NAND gate; open-drain output




Fig 10. Package outline SOT402-1 (TSSOP14)

All information provided in this document is subject to legal disclaimers.

74HC_HCT03

Quad 2-input NAND gate; open-drain output

13. Abbreviations

Table 10. Abbreviations		
Acronym	Description	
CMOS	Complementary Metal-Oxide Semiconductor	
DUT	Device Under Test	
ESD	ElectroStatic Discharge	
НВМ	Human Body Model	
MM	Machine Model	
TTL	Transistor-Transistor Logic	

14. Revision history

Table 11. Revision history

Document ID	Release date	Data sheet status	Change notice	Supersedes	
74HC_HCT03 v.4	20151127	Product data sheet	-	74HC_HCT03 v.3	
Modifications:	 Type numbers 74HC03N and 74HCT03N (SOT27-1) removed. 				
74HC_HCT03 v.3	20130627	Product data sheet	-	74HC_HCT03_CNV v.2	
Modifications:	 The format of this data sheet has been redesigned to comply with the new identity guidelines of NXP Semiconductors. Legal texts have been adapted to the new company name where appropriate. 				
74HC_HCT03_CNV v.2	19970827	Product specification	-	-	

Quad 2-input NAND gate; open-drain output

15. Legal information

15.1 Data sheet status

Document status[1][2]	Product status ^[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions"

The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status [3] information is available on the Internet at URL http://www.nexperia.com

15.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. Nexperia does not give any

representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for guick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local Nexperia sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification - The information and data provided in a Product data sheet shall define the specification of the product as agreed between Nexperia and its customer, unless Nexperia and

customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the Nexperia product is deemed to offer functions and qualities beyond those described in the Product data sheet.

15.3 **Disclaimers**

Limited warranty and liability - Information in this document is believed to be accurate and reliable. However, Nexperia does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. Nexperia takes no responsibility for the content in this document if provided by an information source outside of Nexperia.

In no event shall Nexperia be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, Nexperia's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of Nexperia.

Right to make changes - Nexperia reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use - Nexperia products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of a Nexperia product can reasonably be expected to result in personal injury, death or severe property or environmental damage. Nexperia and its suppliers accept no liability for inclusion and/or use of Nexperia products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. Nexperia makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using Nexperia products, and Nexperia accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the Nexperia product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

Nexperia does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using Nexperia products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). Nexperia does not accept any liability in this respect.

Limiting values - Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale - Nexperia

products are sold subject to the general terms and conditions of commercial sale, as published at http://www.nexperia.com/profile/terms, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. Nexperia hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of Nexperia products by customer.

No offer to sell or license - Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Product data sheet

Quad 2-input NAND gate; open-drain output

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Non-automotive qualified products — Unless this data sheet expressly states that this specific Nexperia product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. Nexperia accepts no liability for inclusion and/or use of

non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without Nexperia's warranty of the

product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond

Nexperia's specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies Nexperia for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond Nexperia's standard warranty and Nexperia's product specifications.

Translations — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

15.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

16. Contact information

For more information, please visit: <u>http://www.nexperia.com</u>

For sales office addresses, please send an email to: salesaddresses@nexperia.com

Quad 2-input NAND gate; open-drain output

17. Contents

1	General description 1
2	Features and benefits 1
3	Ordering information 1
4	Functional diagram 2
5	Pinning information 2
5.1	Pinning
5.2	Pin description 2
6	Functional description 3
7	Limiting values 3
8	Recommended operating conditions 3
9	Static characteristics 4
10	Dynamic characteristics 5
11	Waveforms 6
12	Package outline 8
13	Abbreviations 11
14	Revision history 11
15	Legal information 12
15.1	Data sheet status 12
15.2	Definitions 12
15.3	Disclaimers
15.4	Trademarks 13
16	Contact information 13
17	Contents 14

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Nexperia:

 74HC03D
 74HC03DB
 74HCT03D
 74HCT03DB
 74HCT03N
 74HCT03PW
 74HC03D,652
 74HC03DB,112

 74HC03DB,118
 74HC03D,653
 74HC03N,652
 74HC03PW,112
 74HC03PW,118
 74HCT03D,652
 74HCT03DB,112

 74HCT03DB,118
 74HCT03D,653
 74HCT03N,652
 74HCT03PW,112
 74HCT03PW,118
 74HCT03D,652
 74HCT03DB,112

 74HC03D/AUJ
 74HCT03D,653
 74HCT03N,652
 74HCT03PW,112
 74HCT03PW,118
 74HCT03D/AUJ