**74HC08; 74HCT08** Quad 2-input AND gate Rev. 6 – 13 June 2017

## **1** General description

The 74HC08; 74HCT08 is a quad 2-input AND gate. Inputs include clamp diodes. This enables the use of current limiting resistors to interface inputs to voltages in excess of  $V_{CC}$ .

### 2 Features and benefits

- Complies with JEDEC standard JESD7A
- Input levels:
  - For 74HC08: CMOS level
  - For 74HCT08: TTL level
- ESD protection:
  - HBM JESD22-A114F exceeds 2 000 V
  - MM JESD22-A115-A exceeds 200 V
- Multiple package options
- Specified from -40 °C to +85 °C and from -40 °C to +125 °C

## **3** Ordering information


#### Table 1. Ordering information

Туре	Package				
number	Temperature range	Name	Description	Version	
74HC08D	-40 °C to +125 °C	SO14	plastic small outline package; 14 leads;	SOT108-1	
74HCT08D			body width 3.9 mm		
74HC08DB	-40 °C to +125 °C	SSOP14	plastic shrink small outline package; 14 leads;	SOT337-1	
74HCT08DB			body width 5.3 mm		
74HC08PW	-40 °C to +125 °C	TSSOP14	plastic thin shrink small outline package; 14 leads;	SOT402-1	
74HCT08PW			body width 4.4 mm		
74HC08BQ	-40 °C to +125 °C	DHVQFN14	plastic dual in-line compatible thermal enhanced	SOT762-1	
74HCT08BQ			very thin quad flat package; no leads; 14 terminals; body 2.5 × 3 × 0.85 mm		

# nexperia


Quad 2-input AND gate

## 4 Functional diagram



## **5 Pinning information**

### 5.1 Pinning



#### 5.2 Pin description

Table 2. Pin description						
Symbol	Pin	Description				
1A to 4A	1, 4, 9, 12	data input				
1B to 4B	2, 5, 10,13	data input				
1Y to 4Y	3, 6, 8, 11	data output				
GND	7	ground (0 V)				
V <sub>cc</sub>	14	supply voltage				

#### **Functional description** 6

Table 3. Function table <sup>[1]</sup>							
Input	Output						
nA	nB	nY					
L	L	L					
L	Н	L					
Н	L	L					
Н	Н	Н					

[1] H = HIGH voltage level;

L = LOW voltage level;

X = don't care.

#### **Limiting values** 7

#### Table 4. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134). Voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions	Min	Max	Unit
V <sub>CC</sub>	supply voltage		-0.5	+7	V
I <sub>IK</sub>	input clamping current	$V_1 < -0.5 V \text{ or } V_1 > V_{CC} + 0.5 V$ [	1] _	±20	mA
I <sub>OK</sub>	output clamping current	$V_{\rm O}$ < -0.5 V or $V_{\rm O}$ > $V_{\rm CC}$ + 0.5 V <sup>[</sup>	1] _	±20	mA
lo	output current	$-0.5 V < V_O < V_{CC} + 0.5 V$	-	±25	mA
I <sub>CC</sub>	supply current		-	50	mA
I <sub>GND</sub>	ground current		-50	-	mA
T <sub>stg</sub>	storage temperature		-65	+150	°C
P <sub>tot</sub>	total power dissipation	$T_{amb} = -40 \text{ to } +85 \text{ °C}$	2] _	500	mW

The input and output voltage ratings may be exceeded if the input and output current ratings are observed. [1]

[2] For SO14 package: Ptot derates linearly with 8 mW/K above 70 °C.

For (T)SSOP14 packages: Ptot derates linearly with 5.5 mW/K above 60 °C.

For DHVQFN14 packages:  $\mathsf{P}_{tot}$  derates linearly with 4.5 mW/K above 60 °C.

## 8 Recommended operating conditions

#### Table 5. Recommended operating conditions

Voltages are referenced to GND (ground = 0 V)

Symbol	Parameter	Conditions	ons 74HC08		74HCT08			Unit	
			Min	Тур	Мах	Min	Тур	Мах	
V <sub>CC</sub>	supply voltage		2.0	5.0	6.0	4.5	5.0	5.5	V
VI	input voltage		0	-	V <sub>CC</sub>	0	-	V <sub>CC</sub>	V
Vo	output voltage		0	-	V <sub>CC</sub>	0	-	V <sub>CC</sub>	V
T <sub>amb</sub>	ambient temperature		-40	-	+125	-40	-	+125	°C
Δt/ΔV	input transition rise and fall rate	V <sub>CC</sub> = 2.0 V	-	-	625	-	-	-	ns/V
		V <sub>CC</sub> = 4.5 V	-	1.67	139	-	1.67	139	ns/V
		V <sub>CC</sub> = 6.0 V	-	-	83	-	-	-	ns/V

## 9 Static characteristics

#### Table 6. Static characteristics

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

Symbol	Parameter	Conditions		25 °C		-	°C to 5 °C	-40 °C to +125 °C		Unit
			Min	Тур	Max	Min	Max	Min	Max	
74HC08					1		1	,		
VIH	HIGH-level	V <sub>CC</sub> = 2.0 V	1.5	1.2	-	1.5	-	1.5	-	V
	input voltage	V <sub>CC</sub> = 4.5 V	3.15	2.4	-	3.15	-	3.15	-	V
		V <sub>CC</sub> = 6.0 V	4.2	3.2	-	4.2	-	4.2	-	V
VIL	LOW-level	V <sub>CC</sub> = 2.0 V	-	0.8	0.5	-	0.5	-	0.5	V
	input voltage	V <sub>CC</sub> = 4.5 V	-	2.1	1.35	-	1.35	-	1.35	V
		V <sub>CC</sub> = 6.0 V	-	2.8	1.8	-	1.8	-	1.8	V
V <sub>OH</sub>	HIGH-level	$V_{I} = V_{IH} \text{ or } V_{IL}$								
	output voltage	I <sub>O</sub> = -20 μA; V <sub>CC</sub> = 2.0 V	1.9	2.0	-	1.9	-	1.9	-	V
		$I_{O}$ = -20 µA; V <sub>CC</sub> = 4.5 V	4.4	4.5	-	4.4	-	4.4	-	V
		I <sub>O</sub> = -20 μA; V <sub>CC</sub> = 6.0 V	5.9	6.0	-	5.9	-	5.9	-	V
		I <sub>O</sub> = -4.0 mA; V <sub>CC</sub> = 4.5 V	3.98	4.32	-	3.84	-	3.7	-	V
		I <sub>O</sub> = -5.2 mA; V <sub>CC</sub> = 6.0 V	5.48	5.81	-	5.34	-	5.2	-	V
V <sub>OL</sub>	LOW-level	$V_{I} = V_{IH} \text{ or } V_{IL}$								
	output voltage	I <sub>O</sub> = 20 μA; V <sub>CC</sub> = 2.0 V	-	0	0.1	-	0.1	-	0.1	V
		$I_0$ = 20 µA; $V_{CC}$ = 4.5 V	-	0	0.1	-	0.1	-	0.1	V
		$I_0$ = 20 µA; $V_{CC}$ = 6.0 V	-	0	0.1	-	0.1	-	0.1	V
		I <sub>O</sub> = 4.0 mA; V <sub>CC</sub> = 4.5 V	-	0.15	0.26	-	0.33	-	0.4	V

74HC\_HCT08

## Nexperia

## 74HC08; 74HCT08

## Quad 2-input AND gate

Symbol	Parameter	Conditions		25 °C		-40 °C to +85 °C		-40 °C to +125 °C		Unit
			Min	Тур	Мах	Min	Max	Min	Max	
		I <sub>O</sub> = 5.2 mA; V <sub>CC</sub> = 6.0 V	-	0.16	0.26	-	0.33	-	0.4	V
l <sub>l</sub>	input leakage current	$V_1 = V_{CC}$ or GND; $V_{CC} = 6.0$ V	-	-	±0.1	-	±1	-	±1	μA
I <sub>CC</sub>	supply current	$V_{I} = V_{CC}$ or GND; $I_{O} = 0$ A; $V_{CC} = 6.0$ V	-	-	2.0	-	20	-	40	μA
CI	input capacitance		-	3.5	-	-	-	-	-	pF
74HCT08				1						
V <sub>IH</sub>	HIGH-level input voltage	$V_{CC}$ = 4.5 V to 5.5 V	2.0	1.6	-	2.0	-	2.0	-	V
V <sub>IL</sub>	LOW-level input voltage	$V_{CC}$ = 4.5 V to 5.5 V	-	1.2	0.8	-	0.8	-	0.8	V
V <sub>OH</sub>	HIGH-level	$V_{I}$ = $V_{IH}$ or $V_{IL}$ ; $V_{CC}$ = 4.5 V								
	output voltage	I <sub>O</sub> = -20 μA	4.4	4.5	-	4.4	-	4.4	-	V
		I <sub>O</sub> = -4.0 mA	3.98	4.32	-	3.84	-	3.7	-	V
V <sub>OL</sub>	LOW-level	$V_{I} = V_{IH} \text{ or } V_{IL}; V_{CC} = 4.5 \text{ V}$								_
	output voltage	I <sub>O</sub> = 20 μA	-	0	0.1	-	0.1	-	0.1	V
		I <sub>O</sub> = 5.2 mA	-	0.15	0.26	-	0.33	-	0.4	V
lı	input leakage current	$V_1 = V_{CC}$ or GND; $V_{CC} = 5.5 V$	-	-	±0.1	-	±1	-	±1	μA
I <sub>CC</sub>	supply current	$V_1 = V_{CC}$ or GND; $I_0 = 0$ A; $V_{CC} = 5.5$ V	-	-	2.0	-	20	-	40	μA
ΔI <sub>CC</sub>	additional supply current	per input pin; $V_I = V_{CC} - 2.1 \text{ V}; I_O = 0 \text{ A};$ other inputs at $V_{CC}$ or GND; $V_{CC} = 4.5 \text{ V}$ to 5.5 V	-	60	216	-	270	-	294	μA
CI	input capacitance		-	3.5	-	-	-	-	-	pF

Quad 2-input AND gate

## **10** Dynamic characteristics

#### Table 7. Dynamic characteristics

 $GND = 0 V; C_L = 50 pF;$  for test circuit see Figure 7.

Symbol	Parameter	Conditions			25 °C		-40 °C to	o +125 ℃	Unit
				Min	Тур	Мах	Max (85 °C)	Max (125 °C)	
74HC08						-			
t <sub>pd</sub>	propagation delay	nA, nB to nY; see <u>Figure 6</u>	[1]						
		V <sub>CC</sub> = 2.0 V		-	25	90	115	135	ns
		V <sub>CC</sub> = 4.5 V		-	9	18	23	27	ns
		V <sub>CC</sub> = 5.0 V; C <sub>L</sub> = 15 pF		-	7	-	-	-	ns
		V <sub>CC</sub> = 6.0 V		-	7	15	20	23	ns
t <sub>t</sub>	transition time	see <u>Figure 6</u>	[2]						
		V <sub>CC</sub> = 2.0 V		-	19	75	95	110	ns
		V <sub>CC</sub> = 4.5 V		-	7	15	19	22	ns
		V <sub>CC</sub> = 6.0 V		-	6	13	16	19	ns
C <sub>PD</sub>	power dissipation capacitance	per package; $V_I$ = GND to $V_{CC}$	[3]	-	10	-	-	-	pF
74HCT08		1			1	1	1		
t <sub>pd</sub>	propagation delay	nA, nB to nY; see <u>Figure 6</u>	[1]						
		V <sub>CC</sub> = 4.5 V		-	14	24	30	36	ns
		V <sub>CC</sub> = 5.0 V; C <sub>L</sub> = 15 pF		-	11	-	-	-	ns
t <sub>t</sub>	transition time	$V_{CC}$ = 4.5 V; see <u>Figure 6</u>	[2]	-	7	15	19	22	ns
C <sub>PD</sub>	power dissipation capacitance	per package; V <sub>I</sub> = GND to V <sub>CC</sub> - 1.5 V	[3]	-	20	-	-	-	pF

 $P_{D} = C_{PD} \times V_{CC}^{2} \times f_{i} \times N + \sum (C_{L} \times V_{CC}^{2} \times f_{o}) \text{ where:}$ 

 $f_i$  = input frequency in MHz;


f<sub>o</sub> = output frequency in MHz;

C<sub>L</sub> = output load capacitance in pF;

 $V_{CC}$  = supply voltage in V; N = number of inputs switching;

 $\sum (C_L \times V_{CC}^2 \times f_0) = \text{sum of outputs.}$ 

## **10.1 Waveforms and test circuit**




#### Table 8. Measurement points

Туре	Input	Output			
	V <sub>M</sub>	V <sub>M</sub>	V <sub>X</sub>	V <sub>Y</sub>	
74HC08	0.5V <sub>CC</sub>	0.5V <sub>CC</sub>	0.1V <sub>CC</sub>	0.9V <sub>CC</sub>	
74HCT08	1.3 V	1.3 V	0.1V <sub>CC</sub>	0.9V <sub>CC</sub>	

### Nexperia

## 74HC08; 74HCT08

#### Quad 2-input AND gate



Test data is given in <u>Table 9</u>.

Definitions test circuit:

 $R_T$  = termination resistance should be equal to output impedance  $Z_o$  of the pulse generator.

 $C_{\text{L}}$  = load capacitance including jig and probe capacitance.


Figure 7. Test circuit for measuring switching times

#### Table 9. Test data

Туре	Input Lo		Load	Test
	VI	t <sub>r</sub> , t <sub>f</sub>	CL	
74HC08	V <sub>CC</sub>	6.0 ns	15 pF, 50 pF	t <sub>PLH</sub> , t <sub>PHL</sub>
74HCT08	3.0 V	6.0 ns	15 pF, 50 pF	t <sub>PLH</sub> , t <sub>PHL</sub>

Quad 2-input AND gate


## **11 Package outline**




Product data sheet

9/16


#### Quad 2-input AND gate



### Quad 2-input AND gate



#### Quad 2-input AND gate



Quad 2-input AND gate

## **12 Abbreviations**

Table 10. Abbreviations					
Acronym	Description				
CMOS	Complementary Metal-Oxide Semiconductor				
DUT	Device Under Test				
ESD	ElectroStatic Discharge				
НВМ	Human Body Model				
MM	Machine Model				
TTL	Transistor-Transistor Logic				

## **13 Revision history**

#### Table 11. Revision history

Document ID	Release date	Data sheet status	Change notice	Supersedes				
74HC_HCT08 v.6	20170613	Product data sheet	-	74HC_HCT08 v.5				
Modifications:	Nexperia.	ne format of this data sheet has been redesigned to comply with the identity guidelines of experia. Egal texts have been adapted to the new company name where appropriate.						
74HC_HCT08 v.5	20151130	Product data sheet	-	74HC_HCT08 v.4				
Modifications:	Type numbers 74	4HC08N and 74HCT08N (SC	DT27-1) removed.					
74HC_HCT08 v.4	20120906	Product data sheet	-	74HC_HCT08 v.3				
Modifications:	<ul> <li>The format of this data sheet has been redesigned to comply with the new identity guidelines of NXP Semiconductors.</li> <li>Legal texts have been adapted to the new company name where appropriate.</li> </ul>							
74HC_HCT08 v.3	20030725	Product specification	-	74HC_HCT08_CNV v.2				
74HC_HCT08_CNV v.2	19970826	Product specification	-	-				

## 14 Legal information

### 14.1 Data sheet status

Document status <sup>[1][2]</sup>	Product status <sup>[3]</sup>	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

Please consult the most recently issued document before initiating or completing a design. [1]

The term 'short data sheet' is explained in section "Definitions".

[2] [3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL http://www.nexperia.com.

#### 14.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. Nexperia does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local Nexperia sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between Nexperia and its customer, unless Nexperia and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the Nexperia product is deemed to offer functions and qualities beyond those described in the Product data sheet.

#### 14.3 Disclaimers

Limited warranty and liability - Information in this document is believed to be accurate and reliable. However, Nexperia does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. Nexperia takes no responsibility for the content in this document if provided by an information source outside of Nexperia. In no event shall Nexperia be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory. Notwithstanding any damages that customer might incur for any reason whatsoever, Nexperia's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of Nexperia

Right to make changes - Nexperia reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use - Nexperia products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an Nexperia product can reasonably be expected to result in personal injury, death or severe property or environmental damage. Nexperia and its suppliers accept no liability for inclusion and/or use of Nexperia products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. Nexperia makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification. Customers are responsible for the design and operation of their applications and products using Nexperia products, and Nexperia accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the Nexperia product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products. Nexperia does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using Nexperia products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). Nexperia does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale - Nexperia products are sold subject to the general terms and conditions of commercial sale, as published at http://www.nexperia.com/profile/terms, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. Nexperia hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of Nexperia products by customer

No offer to sell or license - Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

#### Quad 2-input AND gate

Non-automotive qualified products — Unless this data sheet expressly states that this specific Nexperia product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. Nexperia accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications. In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without Nexperia's warranty of the product for such automotive applications, use and specifications beyond Nexperia's specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies Nexperia for any liability, damages or failed product claims resulting from customer

design and use of the product for automotive applications beyond Nexperia's standard warranty and Nexperia's product specifications.

**Translations** — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

#### 14.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

### Nexperia

## 74HC08; 74HCT08

Quad 2-input AND gate

### Contents

1	General description	1
2	Features and benefits	1
3	Ordering information	1
4	Functional diagram	2
5	Pinning information	2
5.1	Pinning	
5.2	Pin description	3
6	Functional description	
7	Limiting values	
8	Recommended operating conditions	4
9	Static characteristics	4
10	Dynamic characteristics	6
10.1	Waveforms and test circuit	7
11	Package outline	
12	Abbreviations	13
13	Revision history	13
14	Legal information	14

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© Nexperia B.V. 2017.

All rights reserved.

For more information, please visit: http://www.nexperia.com For sales office addresses, please send an email to: salesaddresses@nexperia.com

Date of release: 13 June 2017 Document identifier: 74HC\_HCT08

## **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Nexperia:

 74HC08BQ,115
 74HC08D,652
 74HC08DB,112
 74HC08DB,118
 74HC08D,653
 74HC08PW,112
 74HC08PW,118

 74HCT08BQ,115
 74HCT08D,652
 74HCT08DB,112
 74HCT08DB,118
 74HCT08D,653
 74HCT08PW,112

 74HCT08PW,118
 74HC08D/AUJ
 74HCT08DB,112
 74HCT08DB,118
 74HCT08D,653
 74HCT08PW,112

 74HCT08PW,118
 74HC08D/AUJ
 74HCT08D/AUJ
 74HCT08D/AUJ
 74HCT08D/AUJ